

Video Doorbell

Data Sheet

© 2023 Alarm.com. All rights reserved. 221104



Specifications

- **Recording compression:** H.264
- **Ingress protection:** IP65
- **Max resolution:** 1440 x 1440
- **Image sensor:** 1/2.4", 2.36 MP, HDR
- **Lens / angle of view:** 165° horizontal, 145° vertical
- **Low-light sensitivity:** 0 lux with IR
- **IR range:** Up to 15 feet (5 meters)
- **Image adjustments:** Flip, brightness, contrast, saturation, sharpness, exposure
- **Wireless connectivity:** 802.11 b/g/n/ac, 2.4 & 5 GHz
- **Operating temperature:** -58°F - 122°F (-50°C - 50°C)
- **Operating humidity:** < 95% (non-condensing) RH
- **Dimensions:** (W x L x D) 1.5 x 4.81 x 1.18" assembled with back plate (38 x 122 x 30 mm)
- **Activity Detection:** Advanced Video Analytics for People Detection
- **Audio:** Two-Way Audio (Full Duplex)



Overview

This doorbell offers crystal clear 2MP picture and an expansive 165° horizontal and 145° vertical Field of View so customers can see and do more at the front door. Alarm.com's powerful People Detection and crisp Two-Way Audio help reduce false notifications while bringing increased awareness and allowing users to communicate with visitors. Plus a wide range of operating temperatures increase install flexibility making this a great choice in any environment.

Features

- **Expansive 165° horizontal and 145° vertical Field of View** ensures customers get a full picture of what's happening at their front door
- **Video Analytics with rapid People Detection** for faster, more relevant alerts and fewer false notifications
- **Full HD resolution, High Dynamic Range (HDR), and infrared night vision**
- **Two-Way Audio**
- **Compatible with the Alarm.com Smart Chime (W115C)**
- **2MP live video and saved clip viewing via the app and customer website**
- **Dual antenna (2x2 MIMO) Wi-Fi for improved range (2.4 GHz and 5 GHz)**

Included accessories

- Video doorbell
- Wallplate (with pre-assembled set screw and wire terminal screws)
- Wall anchors (x2) & screws (x2)

Status light guide



Off: Power off



Blinking yellow: Camera power cycling



Solid red: No local or Internet connection



Blinking red: Power on, camera booting



Alternating red and green: Camera resetting to factory default



Solid green: Connected to Alarm.com



Blinking green: Local network connection



Blinking blue: WPS mode



Blinking white: Wi-Fi Access Point mode